



FICHA TÉCNICA

Sensor De Luz Fococelda. Switch Interruptor De Encendido Automático Con Sensor De Oscuridad 120V. Interruptor

CÓDIGO:
AB007-AC110V-SR-05



Model No.	SR-05
Rated Voltage	AC100-277V
Rated current	5A
Rated Frequency	50/60Hz
Rated Loading	1000WTungsten, 1800VABallast
Own power consumption Power consumption	1W
Switch light brightness Operate Level	5-300LUX
Ambient Temperature	-40℃~ +70℃
Environmental humidity Related Humidity	99%RH
Overall Dimensions	52(L) x 49(W) x 45.5(H)mm
Leads Length	180mm or Customer request
Degree of protection	IP54

***Nombre:** Switch interruptor de encendido automático con sensor de oscuridad 120V.

Código de producto: AB007-AC110V-SR-05

Marca: GENERICO

Procedencia: Importado

Tipo: Tomacorrientes e Interruptores

INFORMACIÓN ADICIONAL

Switch Interruptor De Encendido Automático Con Sensor De Oscuridad 120V.

Este Producto Es Un Interruptor Automático Controlado Por Luz, Que Se Enciende Automáticamente Cuando Oscurece Y Se Apaga Automáticamente Cuando Amanece. No Requiere Accionamiento Manual, Tiene Un Bajo Consumo Y Ahorra Energía.

- Características

El Producto Puede Encender O Apagar La Luz En Función De La Luz Ambiente; La Temperatura Ambiente Y La Humedad No Pueden Afectarlo. No Sólo Es Conveniente, Sino También Práctico, Puede Controlar La Carga De Trabajo Sólo Por La Noche. Por Ejemplo, Luz De Carretera, Luz De Jardín, Etc.



Model No.	SR-05
Rated Voltage	AC100-277V
Rated current	5A
Rated Frequency	50/60Hz
Rated Loading	1000WTungsten, 1800VABallast
Own power consumption Power consumption	1W
Switch light brightness Operate Level	5-300LUX
Ambient Temperature	-40°C~ +70°C
Environmental humidity Related Humidity	99%RH
Overall Dimensions	52(L) x 49(W) x 45.5(H)mm
Leads Length	130mm or Customer request
Degree of protection	IP54